




MIT
Center for Space Research



Chandra X-Ray Center

MEMORANDUM

April 1, 2005

To: Jonathan McDowell, SDS Group Leader
From: Glenn Allen (SDS) for the ACIS Background Working Group
Subject: acis_make_bkgd
Revision: 1.2
URL: http://space.mit.edu/CXC/docs/memo_acis_make_bkgd_1.2.ps
File: /nfs/cxc/h2/gea/sds/docs/memos/memo_acis_make_bkgd_1.2.tex

1 acis_make_bkgd

1.1 Description

When users analyze the spectral data of a source on some region of an ACIS detector, they should try to estimate the background spectrum using data from a nearby, on-chip, source-free region. The advantages of such a background spectrum are that the background region has experienced essentially the same charged-particle radiation as the source region and that the data from both regions have been processed in the same manner (i.e. using the same CTI, tgain and gain files and using the same set of filter criteria). However, it is not always possible or convenient to use an on-chip background. For example, some extended sources fill the entire field of view of the ACIS instrument. For such sources, there are no source-free regions on the detectors.

The calibration team has prepared some event-data files that can be used to estimate the charged-particle background. This spec describes the algorithm for the tool `acis_make_bkgd`, which can be used to process the background calibration files and create an observation-specific background event-data file. The output is unique to a given observation because it is created using the same WCS, GTI and aspect information as the observation. Once a background file has been created, `dmextract` can be used with some region specification (i.e. the same region specification used to extract the spectral data of the source) to extract a sample background spectrum. Note that the background spectrum will generally have a different EXPOSURE than the source spectrum, but this difference is handled by the spectral-fitting packages Sherpa, ISIS and XSPEC in a manner which is transparent to the user.

1.2 Parameters

1. `infile,f,a,"",,,` "Input source event file with WCS and GTI information"
2. `outfile,f,a,"",,,` "Output background event file"
3. `bkgfile,f,a,"CALDB",,,` "Input background event file or stack (CALDB | <filename>)"
4. `asolfile,f,a,"",,,` "Input source aspect-solution file"
5. `geompar,f,h,"geom",,,` "Parameter file for pixlib geometry files"

6. `energy_min,r,h,7,,`, “Minimum energy of range used for renormalization in keV”
7. `energy_max,r,h,10,,`, “Maximum energy of range used for renormalization in keV”
8. `clobber,b,h,“no”,,`, “Overwrite output event file if it already exists?”
9. `verbose,i,h,0,0,5,`, “Amount of messages produced (0=none, 5=most)”
10. `mode,s,h,“ql”,,`, “q=query, h=do not query and l=save values used”

1.3 Input

1. An event-data file that includes WCS and GTI information (e.g. `acis*evt2.fits`).
2. A background event-data file (e.g. `acis7sD2000-12-01bkgndN0002.fits`)
3. An aspect-solution file (e.g. `pcad*asol1.fits`)
4. Geometry files for `pixlib`.

1.4 Output

1. A background event-data file where the sky coordinates are on the same WCS as the coordinates of the source events.

1.5 Processing

1. Verify that the specified input files exist. If the parameter `clobber = “no,”` then verify that the output file does not exist.
2. Read the WCS information from the input event data file.
3. Read the values of the keywords `SIM_X`, `SIM_Y`, `SIM_Z`, `RA_NOM` and `DEC_NOM` from the aspect solution file.
4. Read the input geometry files.
5. Determine which CCDs were active from the keyword `DETNAM` in the header of the input event-data file. If the keyword is missing, then use the column `CCD_ID` in the `EVENTS` extension of the input event data file to determine the CCDs for which events were reported.
6. Begin a loop over each active CCD.
7. Read the set of GTIs used for `CCD_ID = i`.
8. If the parameter `bkgfile = “CALDB,”` then identify the appropriate input background event-data file to use for `CCD_ID = i`. If there is no file for `CCD_ID = i`, then write a error message and exit.
9. Read the background event data for `CCD_ID = i`.
10. For each background event j ,
 - i Randomly select a `TIME t` for event j from the set GTIs for `CCD_ID = i`. The random deviates should be uniformly distributed within the set of GTIs.
 - ii Determine which values of `RA`, `DEC`, `ROLL`, `dy` and `dz` from the aspect solution file are appropriate for `TIME = t`. If there is no aspect information for `TIME = t`, then write an error message and exit.
 - iii Read the values of `CHIPX`, `CHIPY`, `PHA`, `ENERGY`, `PI`, `FLTGRADE`, `GRADE` and `STATUS` from the input background file for event j .

- iv Use $\text{CCD_ID} = i$, the coordinates CHIPX and CHIPY , the values of RA , DEC , ROLL , dy and dz for $\text{TIME} = t$ and the values of RA_NOM , DEC_NOM , SIM_X , SIM_Y and SIM_Z to compute the values of NODE_ID , TDETX , TDETY , DETX , DETY , X , and Y for event j .
 - v Write the values of TIME , CCD_ID , NODE_ID , CHIPX , CHIPY , TDETX , TDETY , DETX , DETY , X , Y , PHA , ENERGY , PI , FLTGRADE , GRADE and STATUS to the output file. Do not include the column EXPNO in the output file.
11. Set the value of ONTIME_i in the output file equal to the sum of the GTIs for $\text{CCD_ID} = i$. The value of ONTIME_i in the output file is the same as the value of ONTIME_i in the input file because the same set of GTIs for $\text{CCD_ID} = i$ are used. However, the EXPOSURE for the background is generally not the same as the EXPOSURE for the source. Therefore a new keyword called BGDCOR_i (see step 12), which will have to be recognized by dmextract , is included in the output file to compensate for this difference.
 12. Since the charged-particle flux during the source observation may not have been the same as the charged-particle flux during the observations used for the input background file, the EXPOSURE for the output background file is not simply set to be the same as the EXPOSURE in the input background file. The appropriate value of the EXPOSURE in the output file is determined instead by using the relative numbers of counts in input source and background files at the high-energy (i.e. source-free) end of the spectrum. For this reason, set the value of BGDCOR_i in the output file:

$$\text{BGDCOR}_i = \frac{N_{\text{bkg}}}{N_{\text{in}}}, \quad (1)$$

where N_{bkg} is the total number of counts in the input background file such that $\text{CCD_ID} = i$ and $\text{energy_min} \leq \text{ENERGY}/1000 < \text{energy_max}$ and N_{in} is the total number of counts in the input source file such that $\text{CCD_ID} = i$ and $\text{energy_min} \leq \text{ENERGY}/1000 < \text{energy_max}$.

13. Set the value of EXPOSUR_i (and LIVTIME_i) in the output file:

$$\text{EXPOSUR}_i = \text{BGDCOR}_i \times \text{DTCOR} \times \text{ONTIME}_i. \quad (2)$$

The tool dmextract has to recognize the new keywords BGDCOR_i .

14. End the loop over each active CCD.
15. Set the value of ONTIME in the output file to be identical to the value of ONTIME_n , where $\text{CCD_ID} = n$ is the CCD at the aimpoint.
16. Set the value of EXPOSURE (and LIVETIME) in the output file to be identical to the value of EXPOSUR_n , where $\text{CCD_ID} = n$ is the CCD at the aimpoint. Note that the values of EXPOSUR_n can exceed the difference between TSTOP and TSTART .
17. With the following exceptions, the rest of the keywords should be copied from the header of the input source event-data file to the header of the output file.
18. Set $\text{DATAMODE} = \text{FAINT}$ and $\text{READMODE} = \text{TIMED}$ in the output file because this is the mode appropriate for the background data.
19. Set the keyword $\text{FILTER} = \text{NONE}$ in the output file.
20. Set the keyword OBJECT in the output file:

$$\text{OBJECT}_{\text{out}} = \text{OBJECT}_{\text{in}} \text{ BACKGRND}. \quad (3)$$

For example, $\text{OBJECT} = \text{'SN 1006-NE'}$ becomes $\text{OBJECT} = \text{'SN 1006-NE BACKGRND'}$.

21. If the keywords BPIXFILE, CTL_CORR, CTIFILE, GAINFILE, TGAINCOR and TGAINFIL exist in the input background file, then copy the values of these keywords to the output file. Otherwise, exclude the keywords from the output file. If more than one input background file is used and the values of these keywords differ are not the same, then write a warning message and exclude the keywords that differ from the output file.
22. If the values of any of the keywords CTL_CORR, CTIFILE, GAINFILE and TGAINCOR in the input source event-data file differ from the values of the same keywords in the input background file(s), then write a warning message that there may be a mismatch between the pulse height processing of the input event file and the input background file.
23. Exclude the keywords DATE-END, DATE-OBS, OBSERVER, OBS.ID, SEQ_NUM, TIMEPIXR and TITLE from the output file.
24. Add some COMMENTS to the header of the output file, which state that the file is a background file not an event file associated with an observation.
25. TIME sort the output file.
26. Append the GTIs used to the output file.